

H05RN-F/3G1.0
H07RN-F/3G1.5

IP20

MEGAMAN

www.megaman.cc/user-guide

220-240V~

L: BROWN
N: BLUE

10mm

10mm

Cutout: 32-36mm

Neutral

Live

N

PL

N in

L in

LED-BLACK

LED+RED

G+ GREEN

R+YELLOW

S1 WHITE

S2 ORANGE

RED +

-

24h

3h

0%

100%

N

L

MCB

L

N

or

24h


24h

or

FEL70100v0-em

Open Area | 130lm | 0.5lux


Position Height(m)	↔	↔
2.5	5.6	13.5
2.8	4.9	14
3	4.5	14
4	3.1	13.5



FEL70200v0-em

Corridor Area | 130lm | 1lux

Position Height(m)	↔	↔	↔	↔
2.5	1.5	8.75	3.8	20
2.8	1.5	9.2	4.2	21.5
3	1.5	9.4	4.2	22.5
4	1.4	6	4.5	24.5



EMERGENCY LUMINAIRE TEST RECORD

INSTALLATION ENGINEERS TEL

LUMINAIRE TYPE IDENT/SERIAL No

LOCATION INSTALLATION DATE

MONTH	TEST TYPE	FIRST YEAR		SECOND YEAR		THIRD YEAR		FOURTH YEAR		FIFTH YEAR	
		SIGN	DATE	SIGN	DATE	SIGN	DATE	SIGN	DATE	SIGN	DATE
1	FUNCTIONAL										
2	FUNCTIONAL										
3	FUNCTIONAL										
4	FUNCTIONAL										
5	FUNCTIONAL										
6	1 HOUR										
7	FUNCTIONAL										
8	FUNCTIONAL										
9	FUNCTIONAL										
10	FUNCTIONAL										
11	FUNCTIONAL										
12	1 HOUR										
13	FULL DURATION										

DAILY: check charge indicators are lit maintained/combined lamps illuminate; any faults are recorded
 MONTHLY: in addition to the daily check - a functional test of at least 3 minutes duration to confirm lamp is working on battery power by simulating a mains failure.
 SIX MONTHLY: in addition to the daily check - a functional test of at least one hour to confirm lamp is working on battery power by simulating a mains failure.
 ANNUALLY: in addition to the daily check - a functional test of rated duration to confirm full operation to specification by simulating a mains failure.
 A copy of this report must accompany any fitting returned to the manufacturer for any reason.

Caution – Risk of Electric Shock! Vorsicht - GEFAHR EINES STROMSCHLAGS! ATENCIÓN - RIESGO DE DESCARGA ELÉCTRICA! Attenzione - RISCHIO DI SCOSSA ELETTRICA! ATTENTION - RISQUE DE CHOC ÉLECTRIQUE! Voorzichtig - GEVAAR VOOR EEN ELEKTRISCHE SCHOK! POZOR! - Riziko úrazu elektrickým proudem.



The light source contained in this luminaire shall only be replaced by the manufacturer or his service agent or a similar qualified person.
 Das in dieser Leuchte enthaltene Leuchtmittel darf nur durch den Hersteller, seinen Kundendienst oder entsprechend qualifiziertes Fachpersonal ausgetauscht werden.
 La fuente de iluminación de esta luminaria solo debe ser sustituida por el fabricante o su agente de servicio, o en su caso, por una persona cualificada.
 La sorgente luminosa contenuta in questo apparecchio deve essere sostituita esclusivamente dal produttore, dal suo rappresentante o da una persona similmente qualificata.
 La source lumineuse contenue dans ce luminaire ne doit être remplacée que par le fabricant ou son agent de maintenance ou une personne de qualification équivalente.
 De lichtbron in deze lamp mag alleen worden vervangen door de fabrikant, zijn serviceagent of een vergelijkbaar gekwalificeerd persoon.
 Zdroj světla v tomto svítidle smí být vyměněn pouze elektrikářem, nebo servisním agentem výrobce.

	P	I	U							
	1W	150mA	220-240V~	N/A	Ø 38	W ₁ (mm)	W ₂ (mm)	H (mm)	X	Y
FEL70100v0-em	1W	150mA	220-240V~	N/A	Ø 38	100	50	40	IP20	IPxx
FEL70200v0-em	1W	150mA	220-240V~	N/A	Ø 38	100	50	40	IP20	IPxx

