

Compatible Dimmer List



MEGAMAN® LED PAR16 7W
LR4407d-50H24D and LR4407d-50H35D
- MM05118

Dimmer List 220-240V


Manufacturer	Model No.	Voltage (V)	Wattage (W)	Min. Number of LED Lamp(s) Compatible*	Max. Number of LED Lamp(s) Compatible*
ABB	6523U	230	2-100(LED)	1	6
ABB	6524U	230	2-100	1	3
Altenburger	EHR600W	220-240	60-600	1	6
Altenburger	Sim2A	220	60-400	1	6
Anam	ASW 3000-1	220-240	60-1000	1	3
Aurora	AU-DSP400	240	60-400	1	6
Aurora	AU-DSP400X	240	60-400	1	6
Aurora	AU-DSPP400X	230	60-400	1	6
British General	881P-01	240	60-400	1	6
British General	AT091-BG	200-250	60-500	1	6
Broco	F25AF	220-240	60-500	1	6
Bticino	CW20 802	250	400	1	6
Bticino	DG07074	220-240	40-900	1	6
Bticino	L4581	220-230	50-1000	1	6
Bticino	M9350S	220-240	500	1	3
Busch	2210..-510	230	60-400	1	6
Busch	2210-510	220-240	400	1	6
Busch	2250U	220-240	60-600	1	6
Chengli	27V500	250	500	1	6
China IDV	IKT02	220	500	1	3
Click	MD9042	220-240	60-400	1	6
Clipsal	3031V500M/K	250	500	1	6
Clipsal	32E450LM	220-240	20-450	1	6
Clipsal	32E450ULM	220-240	450	1	6
Clipsal	32V 500 Series	220-240	500	1	6
Clipsal	E3032V500	250	500	1	6
Clipsal	EV51RD400	220	400	1	6
Clipsal	KB31-RD400	220-240	400	1	6
Clipsal	S/I/E32	250	500	1	5
Contactum	P400	216-253	60-400	1	6
Crabtree	CPU-2W400	200-240	60-400	1	6
Crabtree	CRO-1W400	220-240	10-600	1	6
Danlers	DG05014	230	60-400	1	6



Manufacturer	Model No.	Voltage (V)	Wattage (W)	Min. Number of LED Lamp(s) Compatible*	Max. Number of LED Lamp(s) Compatible*
Danlers	DP1DLED	230	5-250	1	6
Danlers	DR1D400w	230	60-400	1	6
Denmans	HDP-400	200-240	60-400	1	6
Deta	DEP-250DT	200-240	35-250	1	6
Deta	DEP-400DT	200-240	35-400	1	6
Dimcontrol	CFL-100	230	1000	1	6
Doyle & Tratt Products	7066	220-240	40-250	1	6
Doyle & Tratt Products	P400	220-240	60-400	1	6
Düwi	8050	230	40-400	1	6
Düwi	8085	230	40-400	1	6
Düwi	11442	230	50-300	1	3
Düwi	Grundtyp D1	230	60-300	1	6
Düwi	Grundtyp H1	230	20-500	1	6
Elari	ATD300R	230	300	1	6
Elko	400GLI	220-240	40-400	1	6
ERA	DG07037	220-240	300	1	6
Everflourish	EFO700DA	220-240	50-300	1	6
Everflourish	EFO700DB	230	50-300	1	6
Fungyip	F2771	220-240	500	1	6
GE	37/56	230	40-500	1	6
GET	EN60669	220-240	250	1	6
GET	GET 60-400W	220-240	60-400	1	6
GET	R25E	200-250	60-250	1	6
Gewiss	GW 20 803	230	300	1	6
Gira	03000	230	20-500	1	3
GP	GP300	250	300	1	6
Hamilton	L400/2	220-240	400	1	6
Home Automation	VID dimr100e	200-250	50-500	1	6
Igoto	DG04041	220-240	200	1	3
IKEA	E0902-DIM	220-240	25-150	1	4
Jin Meung (SK)	DG04047	220-240	1000	1	4
Jung	1254 UDE	230	50-420	1	6
Jung	244EX	220-240	60-400	1	6
Keytop	BP1000	220-240	1000	1	4
Kopp	80.33	230	40-400	1	6
Legrand	281 080	230	500	3	6
Legrand	6145 25	220-240	25-250	1	2
Legrand	ADWGL4	220-240	40-400	1	6
Legrand	ADW-GL6	230	60-600	1	6
Legrand	BMD 300	100-240	40-300	1	6
Legrand	Haut 100-1000VA	250	100-1000	1	6



Manufacturer	Model No.	Voltage (V)	Wattage (W)	Min. Number of LED Lamp(s) Compatible*	Max. Number of LED Lamp(s) Compatible*
Legrand	Mosaic	220-240	60-500	1	6
Legrand	Neptune 806 15	230	60-500	1	6
Legrand	YB-CZD	220	40-630	1	6
Lightwave	JSJSLW420SS	230	60(LED)	1	6
LK	506DA117	230	20-300	1	6
Lumeo	Domus T39.07	230	7-110	1	3
Makel	DG07095	230	450	1	6
Mank	MK/TG100001	250	200	1	3
Merlin Gurin	MGU351118	230	400	1	6
Merten	5722	230	60-600	1	6
MK	42804PL	230	40-250	1	6
MK	47352SL	230	60-450	1	6
MK	52471SL	230	60-500	1	6
MK	GX8051	220-240	40-500	1	3
MK	K1523WHILV	230	40-300	1	6
MK	K1524WHILV	230	4-70	1	1
MK	K1526WHI	230	8-48	1	1
MK	K1527WHI	230	8-48	1	1
MK	K4511LV	220-240	4-70	1	1
MK	L/N1511	230	60-450	1	6
MK	SX8051	240	40-500	1	4
National	WEC57515	220	40-500	1	6
National	WNG575253	220-240	60-600	1	6
National	WNG6801	220-240	500	1	6
Niko	09-013	230	60-300	1	6
Niko	310-016	220-240	50-500	1	6
Nisko	DG08050	220-240	1000	1	6
Norvika	200074	250	30-500	1	6
Panasonic	WEJ57515	220	40-500	1	6
Peha	434	230	60-400	1	6
Peha	431 HAN LED	230	6-120	1	3
Peha	435 HAN	230	60-600	1	6
POL	CAT 1593M	220-240	500	1	6
Richi	270.15	220	300	1	6
Richmond	MP500	230	40-400	1	6
Richmond	GRID500	240	40-500	1	6
RPP	RPP-DSP250	240	40-250	1	6
RPP	RPP-DSP400X	240	60-400	1	6
Schneider	5510X	220	800	1	6
Schneider	ATTD1000RL	230	60-1000	1	6
Schneider	GU6012	220-240	60-400	1	6
Schneider	LTD300	230	300	1	1



Manufacturer	Model No.	Voltage (V)	Wattage (W)	Min. Number of LED Lamp(s) Compatible*	Max. Number of LED Lamp(s) Compatible*
Schneider	SBD SPL	230	9-100	1	3
Schneider	SD300	220-240	300	1	6
Schneider	WDE002747	230	9-100	1	3
Sica	359901	220	100	1	3
Siemens	5UH8722-3NCO3	230	25-400	1	3
Siemens	Vista	220	500	1	6
Simon	45E101	220	500	1	6
Simon	75313-39	230	40-500	1	6
Simon	Simon..813	220-240	40-500	1	6
Soben	C8M2	200-250	630	1	3
Soben	DG07079	220-240	630	1	6
Switchlight	SW-316	220-240	500	1	2
T&J	EC211-1KM2	230	25-1000	1	3
T&J	K211-M2 6L29	230	40-630	1	1
T&J	P2017S	220-240	40-630	1	5
TCL	KGM2	220-240	500	1	6
TCL	LM2	220	630	1	6
Teclastar	45291	220	500	1	6
TLC	LV LMOD1	216-253	120	1	3
TLC	VL JP400MOD	230	10-250	1	6
Varilight	JQP401W	230	10-400	1	6
Varilight	TQP501W	216-253	60-500	1	6
Venus	ART:9720	220	40-900	1	6
Vi-ko	215	220-240	600	1	4
Vi-ko	90 30 48	220	600	1	6
Vilts plus	WPDIMWH401	230	7-40	1	1
Vimar	Plana 14150	230	100-500	1	6
Vivian	D-21102	220-240	1000	1	6
V-PRO	BS EN 55015	230	400	1	6
Wonpro	WF Series	250	500	1	3
Zano	ZGRID500	230	500	1	3

*Remarks: The minimum and maximum number of LED lamps compatible depends upon the performance of the dimmer, which is subject to the status of the manufacturer's technology. Due to possible variations in country dimmer module specifications, please contact your local distributor for a list of compatible dimmers before installation. Copyright © MEGAMAN® 2015. All rights reserved.

All the information contained within this publication was correct at the time of update and is subject to change without prior notice. All other trademarks mentioned are the property of their respective owners.